



For Professional Use Only

AmpliSens® Candida albicans-FEP PCR kit Instruction Manual

AmpliSens®



Ecoli s.r.o., Studenohorska 12 841 03 Bratislava 47 Slovak Republic

Tel.: +421 2 6478 9336 Fax: +421 2 6478 9040



Federal Budget Institute of Science "Central Research Institute for Epidemiology" 3A Novogireevskaya Street Moscow 111123 Russia

TABLE OF CONTENTS

| 1. INTENDED USE | 3 |
|-------------------------------|----|
| 2. PRINCIPLE OF PCR DETECTION | 3 |
| 3. CONTENT | 3 |
| 4. ADDITIONAL REQUIREMENTS | 4 |
| 5. GENERAL PRECAUTIONS | |
| 6. SAMPLING AND HANDLING | 6 |
| 7. WORKING CONDITIONS | |
| 8. PROTOCOL | 6 |
| 9. DATA ANALYSIS | |
| 10. TROUBLESHOOTING | |
| 11. TRANSPORTATION | |
| 12. STABILITY AND STORAGE | |
| 13. SPECIFICATIONS | 9 |
| 14. REFERENCES | |
| 15. QUALITY CONTROL | 10 |
| 16 KEY TO SYMBOLS USED | 11 |

1. INTENDED USE

AmpliSens® *Candida albicans*-FEP PCR kit is an *in vitro* nucleic acid amplification test for qualitative detection of *Candida albicans* DNA in clinical materials (urogenital and pharyngeal swabs and urine samples) by using end-point hybridization-fluorescence detection of amplified products.



The results of PCR analysis are taken into account in complex diagnostics of disease.

2. PRINCIPLE OF PCR DETECTION

Candida albicans detection by the polymerase chain reaction (PCR) is based on the amplification of pathogen genome specific region using specific Candida albicans primers. In Fluorescent End-Point PCR, the amplified product is detected by using fluorescent dyes. These dyes are linked to oligonucleotide probes, which bind specifically to the amplified product during thermocycling. A multichannel rotor-type fluorometer is specially designed to detect fluorescence emission from the fluorophores in a reaction mixture after PCR. It allows detection of the accumulating product without re-opening the reaction tubes after the PCR run. AmpliSens® Candida albicans-FEP PCR kit is a qualitative test that contains the Internal Control (IC). It must be used in the extraction procedure in order to control the extraction process of each individual sample and to identify possible reaction inhibition. AmpliSens® Candida albicans-FEP PCR kit uses "hot-start," which greatly reduces the frequency of nonspecifically primed reactions. "Hot-start" is guaranteed by separation of nucleotides and Taq-polymerase by using a chemically modified polymerase (TaqF). Wax melts and reaction components mix only at 95 °C.

3. CONTENT

AmpliSens® Candida albicans-FEP PCR kit is produced in 2 forms:

AmpliSens® Candida albicans-FEP PCR kit variant FEP (0.5-ml tubes),

REF F1-100-R0,5-FEP-CE.

AmpliSens® Candida albicans-FEP PCR kit variant FEP (0.2-ml tubes),

REF F1-100-R0,2-FEP-CE.

AmpliSens® Candida albicans-FEP PCR kit includes:

| Reagent | Description | Volume (ml) | Quantity |
|---|--------------------------|-------------|----------------------------|
| PCR-mix-1-FL Candida albicans (ready-to-use single-dose test tubes (under wax)) | colorless clear liquid | 0.01 | 110 tubes of 0.5 or 0.2 ml |
| PCR-mix-2-FL-red | red clear liquid | 1.1 | 1 tube |
| Mineral oil for PCR* | colorless viscous liquid | 4.0 | 1 dropper bottle |
| PCR-mix-Background-red** | red clear liquid | 0.6 | 1 tube |
| Positive Control complex (C+) | colorless clear liquid | 0.2 | 1 tube |
| DNA-buffer | colorless clear liquid | 0.5 | 1 tube |
| Negative Control (C-)*** | colorless clear liquid | 1.2 | 1 tube |
| Internal Control-FL (IC)**** | colorless clear liquid | 1.0 | 1 tube |

^{*} is used for thermocyclers without constant-temperature cover.

**** add 10 µl of Internal Control-FL (IC) during the DNA extraction procedure directly to the sample/lysis mixture (DNA-sorb-AM **REF** K1-12-100-CE).

AmpliSens® Candida albicans-FEP PCR kit is intended for 110 reactions (including controls).

4. ADDITIONAL REQUIREMENTS

- DNA extraction kit.
- Transport medium.
- Disposable powder-free gloves and laboratory coat.
- Pipettes (adjustable).
- Sterile pipette tips with aerosol barriers (up to 200 μl).
- Tube racks.
- Vortex mixer.
- Desktop centrifuge with rotor for 2-ml reaction tubes.
- PCR box.
- Personal thermocyclers (for example, Gradient Palm Cycler (Corbett Research, Australia), GeneAmp PCR System 2700 (Applied Biosystems, USA), MaxyGene (Axygen, USA) or equivalent).

^{**} is used to analyze DNA samples extracted with DNA-sorb-AM and DNA-sorb-B extraction kits.

^{***} must be used in the extraction procedure as Negative Control of Extraction.

- Fluorometer (for example, ALA-1/4 (Biosan, Latvia) or equivalent).
- Personal computer.
- Disposable polypropylene microtubes for PCR (0.5- or 0.2-ml) (for example, Axygen, USA).
- Refrigerator for 2–8 °C.
- Deep-freezer for ≤ -16 °C.
- Waste bin for used tips.

5. GENERAL PRECAUTIONS

The user should always pay attention to the following:

- Use sterile pipette tips with aerosol barriers and use new tip for every procedure.
- Store and handle amplicons away from all other reagents.
- Thaw all components thoroughly at room temperature before starting detection.
- When thawed, mix the components and centrifuge briefly.
- Use disposable gloves, laboratory coats, and protect eyes while samples and reagents handling. Thoroughly wash hands afterwards.
- Do not eat, drink, smoke, apply cosmetics, or handle contact lenses in laboratory work areas.
- Do not use a kit after its expiration date.
- Dispose of all samples and unused reagents in compliance with local authorities' requirements.
- Samples should be considered potentially infectious and handled in a biological cabinet in accordance with appropriate biosafety practices.
- Clean and disinfect all sample or reagent spills using a disinfectant, such as 0.5 % sodium hypochlorite or another suitable disinfectant.
- Avoid contact with the skin, eyes, and mucosa. If skin, eyes, or mucosa contact, immediately flush with water and seek medical attention.
- Material Safety Data Sheets (MSDS) are available on request.
- Use of this product should be limited to personnel trained in the techniques of DNA amplification.
- The laboratory process must be one-directional, it should begin in the Extraction Area and then move to the Amplification and Detection Areas. Do not return samples, equipment and reagents to the area in which the previous step was performed.



Some components of this kit contain sodium azide as a preservative. Do not use metal tubing for reagent transfer.

6. SAMPLING AND HANDLING



Obtaining samples of biological materials for PCR-analysis, transportation and storage are described in manufacturer's handbook [1]. It is recommended that this handbook is read before starting work.

AmpliSens® *Candida albicans*-FEP PCR kit is intended for analysis of DNA extracted by using DNA extraction kits from urogenital and pharyngeal swabs and urine sediment (use the first portion of the morning specimen).

7. WORKING CONDITIONS

AmpliSens® Candida albicans-FEP PCR kit should be used at 18-25 °C.

8. PROTOCOL

8.1 DNA extraction

It is recommended to use the following nucleic acid extraction kits:

• DNA-sorb-AM, **REF** K1-11-100-CE.



Extract DNA according to the manufacturer's instructions.

8.2 Preparing PCR

The total reaction volume is **30** μ **I**, the volume of DNA sample is **10** μ **I**.

8.2.1 Preparing tubes for PCR

- 1. Prepare the required number of tubes with **PCR-mix-1-FL** *Candida albicans* for amplification of DNA from clinical and control samples.
- 2. Add **10 µl** of **PCR-mix-2-FL-red** to the surface of the wax layer of each tube ensuring that it does not fall under the wax and mix with **PCR-mix-1-FL** *Candida albicans*.
- 3. Add above 1 drop of mineral oil for PCR (about 25 μ I) if a thermocycler without constant-temperature cover is used.
- 4. Prepare one Background sample. To do this, mark one PCR-mix-1-FL Candida albicans tube as Background and add 20 μl of PCR-mix-Background-red above the wax layer surface ensuring that it does not fall under the wax and mix with PCR-mix-1-FL Candida albicans. Add above 1 drop of mineral oil for PCR (if a thermocycler without a constant-temperature cover is used).



PCR-mix-Background-red is used if DNA was extracted using DNA-sorb-AM (REF K1-12-100-CE) or DNA-sorb-B (REF K1-2-100-CE). If any other nucleic acid extraction kit (recommended by CRIE) was used, follow the instructions provided by the manufacturer.

5. Add **10 μl** of **DNA samples** obtained from clinical or control samples at the DNA extraction stage using tips with aerosol barrier.

- 6. Carry out the control amplification reactions:
- NCA Add **10** µI of **DNA-buffer** to the tube labeled NCA (Negative Control of Amplification).
- C+ Add **10 μl** of **Positive Control complex** to the tube labeled C+ (Positive Control of Amplification).
- C- Add 10 μI of sample isolated from Negative Control to the tube labeled C-(Negative Control of Extraction).

8.2.2 Amplification

Run the program **AmpliSens-1-FEP amplification program** on the thermocycler (see Table 1).

When the temperature reaches 95°C (pause mode), insert tubes into cells of the thermocycler and press the button to continue.



It is recommended to sediment drops from walls of tubes by short centrifugation (1–3 s) before placing them in the thermocycler.

Table 1

AmpliSens-1-FEP amplification program

| | GeneAmp PCR System 2700 (Applied Biosystems, USA) | | Resea | Palm Cycler arch, Austra ene (Axygen | alia), | |
|------|--|------------|--------|--|--------|--------|
| Step | Temperature, °C | Time | Cycles | Temperature, °C | Time | Cycles |
| 0 | 95 | Pause | | 95 | Pa | ause |
| 1 | 95 | 5 min | 1 | 95 | 5 min | 1 |
| | 95 | 20 s | | 95 | 2 s | |
| 2 | 65 | 25 s | 20 | 65 | 10 s | 24 |
| | 72 | 30 s | | 72 | 10 s | |
| | 95 | 20 s | | 95 | 2 s | |
| 3 | 60 | 30 s | 24 | 60 | 15 s | 20 |
| | 72 | 30 s | | 72 | 10 s | |
| 4 | 95 | 20 s | 1 | 95 | 2 s | 1 |
| 4 | 60 | 30 s | 1 ' | 60 | 15 s | l |
| 5 | 10 | 10 storage | | 10 | sto | rage |

After amplification program run finishes analyze and record results.

9. DATA ANALYSIS

Detection is conducted using a fluorescence detector.



Please read the fluorescence detector Operating Manual before use of this kit.



Detection can be conducted within 1 day after completion of amplification only if the tubes with the amplified product have been stored at 2–8 °C in a light-free area.

Program the detector according to the manufacturer's manual and Guidelines.

- the signal from the *Candida albicans* DNA amplification product is detected in the FAM channel (or analogous, depending on the detector model);
- the signal from the IC amplification product is detected in the HEX channel (or analogous, depending on the detector model).

Principle of interpretation:

- 1. Candida albicans DNA is **detected** in a sample if its signal in the FAM channel is greater than the defined threshold value of the positive result.
- 2. Candida albicans DNA is **not detected** in a sample if the signal in the FAM channel is less than the defined threshold value of the negative result whereas the signal in the HEX channel is greater than the defined threshold value.
- 3. The result is **invalid** in a sample if the signal in the FAM channel is less than the defined threshold value of the negative result whereas the signal in the HEX channel is less than the defined threshold value.
- 4. The result is **equivocal** if the signal of a sample in the FAM channel is greater than the defined threshold value of the negative result but less than the threshold value of the positive result (the signal is between thresholds).



If the result is invalid or equivocal, the PCR should be repeated once again.

The result of the analysis is considered reliable only if the results obtained for both Positive and Negative Controls of amplification as well as for the Negative Control of extraction are correct (Table 2).

Table 2

Results for controls

| Stage for | | Result of automatic inte | | |
|-----------|---------------------|--------------------------------|---------------------|----------------|
| Control | control | FAM channel (samples) | HEX channel (IC) | Interpretation |
| | DNIA system at lase | , , , | | " " an Ol |
| C- | DNA extraction | < threshold of negative result | > threshold | "–" or OK |
| NCA | Amplification | < threshold of negative result | < threshold | "nd" |
| C+ | Amplification | > threshold of positive result | > threshold | "+" or OK |

10. TROUBLESHOOTING

Results of analysis are not taken into account in the following cases:

1. No positive signal in the positive control of amplification (C+) may indicate incorrect programming of the temperature profile of the thermocycler, incorrect configuration of PCR, noncompliance of the storage conditions for kit components with the manufacturer's instruction, or the expiration of the reagent kit. Check programming of the thermocycler (see 8.2.2.), storage conditions, and the expiration date of the reagents and repeat PCR once again for all samples.

- 2. If no signal was detected either in the channel for detection of the pathogen DNA or in the channel for detection of the Internal Control, the sample should be examined once again (PCR and detection). The same applies to the samples with equivocal results, because the fact that the specific signal does not exceed the threshold value is not sufficient to consider a sample as positive. If equivocal results are obtained in the second run, the analysis should be repeated starting from the DNA extraction stage.
- 3. Positive signal in negative controls (C- and NCA) indicates reagent or sample contamination. In this case, the results of analysis must be considered as invalid. The analyses must be repeated and measures for detecting and eliminating the contamination source must be taken.

If you have any further questions or if encounter problems, please contact our Authorized representative in the European Community.

11. TRANSPORTATION

AmpliSens® Candida albicans-FEP PCR kit should be transported at 2–8 °C for no longer than 5 days.

12. STABILITY AND STORAGE

All components of the **AmpliSens**[®] *Candida albicans*-FEP PCR kit are to be stored at 2–8 °C when not in use. All components of the **AmpliSens**[®] *Candida albicans*-FEP PCR kit are stable until the expiration date on the label. The shelf life of opened reagents is the same as that of unopened reagents, unless otherwise stated.



PCR-mix-1-FL Candida albicans should be kept away from light.

13. SPECIFICATIONS

13.1. Sensitivity

The analytical sensitivity of AmpliSens® Candida albicans-FEP PCR kit is following:

| Clinical material | Nucleic acid extraction kit | Sensitivity, GE/ml ¹ |
|-------------------------------|-----------------------------|---------------------------------|
| Urogenital swabs ² | DNA-sorb-AM | 1x10 ³ |

¹ Genome equivalents (GE) of the microorganism per 1 ml of a clinical sample placed in the transport medium specified.

² Urogenital swabs are to be placed into the Transport Medium for Swabs (**REF** 956, 987) or Transport Medium with Mucolytic (**REF** 952, 953)

| Urine ³ | DNA-sorb-AM | 2x10³ |
|--------------------|-------------|-------|
|--------------------|-------------|-------|

13.2. Specificity

The analytical specificity of AmpliSens® Candida albicans-FEP PCR kit is ensured by selection of specific primers and probes as well as strict reaction conditions. The primers and probes were checked for possible homologies to all sequences deposited in gene banks by sequence comparison analysis. Nonspecific reactions were absent while testing human DNA samples and DNA panel of the following microorganisms: Gardnerella vaginalis, Lactobacillus spp., Escherichia coli, Candida glabrata, Candida krusei, Staphylococcus aureus, Streptococcus pyogenes, Streptococcus agalactiae, Mycoplasma hominis, Ureaplasma urealyticum, Ureaplasma parvum, Mycoplasma genitalium, Neisseria flava, Neisseria subflava, Neisseria sicca, Neisseria mucosa, Neisseria gonorrhoeae, Trichomonas vaginalis, Treponema pallidum, Toxoplasma gondii, HSV types 1 and 2, CMV, and HPV. The clinical specificity of AmpliSens® Candida albicans-FEP PCR kit was confirmed in laboratory clinical trials.

14. REFERENCES

- Handbook "Sampling, Transportation, and Storage of Clinical Material for PCR Diagnostics", developed by Federal Budget Institute of Science "Central Research Institute for Epidemiology" of Federal Service for Surveillance on Consumers' Rights Protection and Human Well-Being, Moscow, 2008.
- Guidelines "End-Point PCR Detection of STIs and Other Reproductive Tract Infections", developed by Federal Budget Institute of Science "Central Research Institute for Epidemiology" of Federal Service for Surveillance on Consumers' Rights Protection and Human Well-Being, Moscow.

15. QUALITY CONTROL

In compliance with Federal Budget Institute of Science "Central Research Institute for Epidemiology" ISO 13485-Certified Quality Management System, each lot of **AmpliSens®** *Candida albicans*-FEP PCR kit has been tested against predetermined specifications to ensure consistent product quality.

³ Treatment is required.

16. KEY TO SYMBOLS USED

| . KLI 10311 | WIDOLS USED | | |
|-------------|---|-------------|--------------------------------------|
| REF | Catalogue number | \triangle | Caution |
| LOT | Batch code | Σ | Sufficient for |
| IVD | In vitro diagnostic medical device | | Expiration Date |
| VER | Version | i | Consult instructions for use |
| | Temperature limitation | | Keep away from sunlight |
| | Manufacturer | NCA | Negative control of amplification |
| | Date of manufacture | C- | Negative control of extraction |
| EC REP | Authorised representative in the European Community | C+ | Positive control of Amplification |
| FBIS CRIE | Federal Budget Institute of Science "Central Research Institute for Epidemiology" | IC | Internal control |

List of Changes Made in the Instruction Manual

| VER | Location of changes | Essence of changes |
|----------------|---------------------|--|
| 24.06.11 LA | Cover page, text | The name of Institute was changed to Federal Budget Institute of Science "Central Research Institute for Epidemiology" |