



For Professional Use Only

# AmpliSens® *Mycoplasma genitalium*-FEP PCR kit Instruction Manual

# **AmpliSens**®



Ecoli s.r.o., Studenohorska 12 841 03 Bratislava 47 Slovak Republic

Tel.: +421 2 6478 9336 Fax: +421 2 6478 9040



Federal Budget Institute of Science "Central Research Institute for Epidemiology" 3A Novogireevskaya Street Moscow 111123 Russia

## **TABLE OF CONTENTS**

1. INTENDED USE	
2. PRINCIPLE OF PCR DETECTION	3
3. CONTENT	
4. ADDITIONAL REQUIREMENTS	4
5. GENERAL PRECAUTIONS	
6. SAMPLING AND HANDLING	
7. WORKING CONDITIONS	
8. PROTOCOL	
9. DATA ANALYSIS	7
10. TROUBLESHOOTING	8
11. TRANSPORTATION	
12. STABILITY AND STORAGE	
13. SPECIFICATIONS	
14. REFERENCES	10
15. QUALITY CONTROL	10
16. KEY TO SYMBOLS USED	11

#### 1. INTENDED USE

**AmpliSens®** *Mycoplasma genitalium*-FEP PCR kit is an *in vitro* nucleic acid amplification test for qualitative detection of *Mycoplasma genitalium* DNA in clinical materials (urogenital, rectal, and pharyngeal swabs; mouth cavity discharge; vesicular discharge; and discharge of erosive-ulcer lesions of human skin and mucous membranes) by using end-point hybridization-fluorescence detection of amplified products.



The results of PCR analysis are taken into account in complex diagnostics of disease.

#### 2. PRINCIPLE OF PCR DETECTION

Mycoplasma genitalium detection by the polymerase chain reaction (PCR) is based on the amplification of pathogen genome specific region using specific Mycoplasma genitalium primers. In Fluorescent End-Point PCR, the amplified product is detected by using fluorescent dyes. These dyes are linked to oligonucleotide probes that bind specifically to the amplified product during thermocycling. A multichannel rotor-type fluorometer is specially designed to detect fluorescence emission from the fluorophores in a reaction mixture after PCR. It allows detection of the accumulating product without re-opening the reaction tubes after the PCR run. AmpliSens® Mycoplasma genitalium-FEP PCR kit is a qualitative test that contains the Internal Control (IC). It must be used in the extraction procedure in order to control the extraction process of each individual sample and to identify possible reaction inhibition. AmpliSens® Mycoplasma genitalium-FEP PCR kit uses "hot-start," which greatly reduces the frequency of nonspecifically primed reactions. "Hot-start" is guaranteed by separation of nucleotides and Taq-polymerase by using a wax layer. Wax melts and reaction components mix only at 95 °C.

#### 3. CONTENT

AmpliSens<sup>®</sup> *Mycoplasma genitalium*-FEP PCR kit is produced in 2 forms:

AmpliSens<sup>®</sup> *Mycoplasma genitalium*-FEP PCR kit variant FEP (0.5-ml tubes),

**REF** B4-100-R0,5-FEP-CE.

AmpliSens® Mycoplasma genitalium-FEP PCR kit variant FEP (0.2-ml tubes),

**REF** B4-100-R0,2-FEP-CE.

# AmpliSens® Mycoplasma genitalium-FEP PCR kit includes:

Reagent	Description	Volume (ml)	Quantity
PCR-mix-1-FL Mycoplasma genitalium (ready-to-use single- dose test tubes (under wax))	colorless clear liquid	lorless clear liquid 0.01 110 tube 0.5 or 0.2	
PCR-mix-2-FL-red	red clear liquid	uid 1.1 1 tube	
Mineral oil for PCR*	colorless viscous liquid	4.0	1 dropper
PCR-mix-Background-red**	red clear liquid	0.6	1 tube
Positive Control complex (C+)	colorless clear liquid	0.2	1 tube
DNA-buffer	colorless clear liquid	0.5	1 tube
Negative Control (C-)***	colorless clear liquid	1.2	1 tube
Internal Control-FL (IC)****	colorless clear liquid	1.0	1 tube

is used for thermocyclers without constant-temperature cover (for example, Terzik (DNA-Technology)).

\*\*\*\*add 10 µl of Internal Control-FL (IC) during the DNA extraction procedure directly to the sample/lysis mixture (DNA-sorb-AM **REF** K1-12-100-CE or DNA-sorb-B, **REF** K1-2-100-CE).

AmpliSens® *Mycoplasma genitalium*-FEP PCR kit is intended for 110 reactions (including controls).

#### 4. ADDITIONAL REQUIREMENTS

- DNA extraction kit.
- Transport medium.
- Disposable powder-free gloves and laboratory coat.
- Pipettes (adjustable).
- Sterile pipette tips with aerosol barriers (up to 200 µl).
- Tube racks.
- Vortex mixer.
- Desktop centrifuge with a rotor for 2-ml tubes.
- PCR box.
- Personal thermocyclers (for example, Gradient Palm Cycler (Corbett Research, Australia), GeneAmp PCR System 2700 or GeneAmp PCR System 2400 (Applied Biosystems, USA), Uno-2 (Biometra, Germany), MiniCycler, PTC-100 (MJ Research, USA), MaxyGene (Axygen, USA) or equivalent).

<sup>\*\*</sup> is used to analyze DNA samples extracted with DNA-sorb-AM and DNA-sorb-B extraction kits.

<sup>\*\*\*</sup> must be used in the extraction procedure as Negative control of extraction.

- Fluorometer (for example, ALA-1/4 (Biosan, Latvia) or equivalent).
- Personal computer.
- Disposable polypropylene microtubes for PCR (0.5- or 0.2-ml; for example, Axygen, USA).
- Refrigerator for 2–8 °C.
- Deep-freezer for ≤ -16 °C.
- Waste bin for used tips.

#### 5. GENERAL PRECAUTIONS

The user should always pay attention to the following:

- Use sterile pipette tips with aerosol barriers and use new tip for every procedure.
- Store and handle amplicons away from all other reagents.
- Thaw all components thoroughly at room temperature before starting detection.
- When thawed, mix the components and centrifuge briefly.
- Use disposable gloves, laboratory coats, and protect eyes while samples and reagents handling. Thoroughly wash hands afterwards.
- Do not eat, drink, smoke, apply cosmetics, or handle contact lenses in laboratory work areas.
- Do not use a kit after its expiration date.
- Dispose of all samples and unused reagents in compliance with local authorities' requirements.
- Samples should be considered potentially infectious and handled in a biological cabinet in accordance with appropriate biosafety practices.
- Clean and disinfect all sample or reagent spills using a disinfectant, such as 0.5 % sodium hypochlorite or another suitable disinfectant.
- Avoid contact with the skin, eyes, and mucosa. If skin, eyes, or mucosa contact, immediately flush with water and seek medical attention.
- Material Safety Data Sheets (MSDS) are available on request.
- Use of this product should be limited to personnel trained in the techniques of DNA amplification.
- The laboratory process must be one-directional, it should begin in the Extraction Area and then move to the Amplification and Detection Area. Do not return samples, equipment, and reagents to the area in which the previous step was performed.



Some components of this kit contain sodium azide as a preservative. Do not use metal tubing for reagent transfer.

#### 6. SAMPLING AND HANDLING



Obtaining samples of biological materials for PCR-analysis, transportation and storage are described in manufacturer's handbook [1]. It is recommended that this handbook is read before starting work.

**AmpliSens®** *Mycoplasma genitalium*-FEP PCR kit is intended for analysis of DNA extracted by using DNA extraction kits from urogenital swabs, urine sediment (the first part of the stream), or the prostate gland secretion.

#### 7. WORKING CONDITIONS

AmpliSens® Mycoplasma genitalium-FEP PCR kit should be used at 18-25 °C.

#### 8. PROTOCOL

#### 8.1 DNA extraction

It is recommended to use the following nucleic acid extraction kit:

- DNA-sorb-AM, REF K1-11-100-CE.
- DNA-sorb-B, **REF** K1-2-100-CE (for the prostate gland secretion).



Extract DNA according to the manufacturer's instructions.

#### 8.2 Preparing PCR

The total reaction volume is **30 \muI**, the volume of DNA sample is **10 \muI**.

#### 8.2.1 Preparing tubes for PCR

- Prepare the required number of tubes with PCR-mix-1-FL Mycoplasma genitalium and wax for amplification of DNA from clinical and control samples.
- Add 10 μI of PCR-mix-2-FL-red to the surface of the wax layer of each tube ensuring that it does not fall under the wax and mix with PCR-mix-1-FL Mycoplasma genitalium.
- 3. Add above **1 drop** of **mineral oil for PCR** (about **25 μl**) if a thermocycler without constant-temperature lid is used.
- 4. Prepare one Background sample. To do this, mark one PCR-mix-1-FL Mycoplasma genitalium tube as Background and add 20 μl of PCR-mix-Background-red above the wax layer surface ensuring that it does not fall under the wax and mix with PCR-mix-1-FL Mycoplasma genitalium. Add above 1 drop of mineral oil for PCR (if a thermocycler without a constant-temperature lid is used).



PCR-mix-Background-red is used if DNA was extracted using DNA-sorb-AM (**REF** K1-12-100-CE) or DNA-sorb-B (**REF** K1-2-100-CE). If any other nucleic acid extraction kit (recommended by FBIS CRIE) was used, follow the instructions provided by the manufacturer.

5. Add **10 μl** of **DNA samples** obtained from clinical or control samples at the DNA **REF** B4-100-R0,5-FEP-CE; **REF** B4-100-R0,2-FEP-CE / **VER** 06.07.10–02.07.11 / Page 6 of 12

extraction stage using tips with aerosol barrier.



The tubes with PCR-mix-1-FL *Mycoplasma genitalium* that are not used at the moment should be stored away from light.

6. Carry out the control amplification reactions:

NCA -Add **10** µI of **DNA-buffer** to the tube labeled NCA (Negative Control of Amplification).

C+ -Add **10 μI** of **Positive Control complex** to the tube labeled C+ (Positive Control of Amplification).

#### 8.2.2 **Amplification**

Run the following program in the thermocycler (see Table 1). When the temperature reaches 95 °C (pause mode), insert tubes into the thermocycler cells and press the button to continue.

It is recommended to sediment drops from walls of tubes by short centrifugation (1–3 s) before placing them in the thermocycler.

AmpliSens-1-FEP amplification program

Table 1

	T	erzik		GeneAmp PC	CR Syste	m 2700	<b>Gradient Paln</b>	n Cycler	(Corbett
	(DNA-Te	echnology	<b>'</b> )	(Applied Biosystems)		ms)	Research)		
Step	Temperature	Time	Cycles	Temperature	Time	Cycles	Temperature	Time	Cycles
0	95 °C	pau	se	95 °C	pai	use	95 °C	pai	use
1	95 °C	5 min	1	95 °C	5 min	1	95 °C	5 min	1
	95 °C	2 s		95 °C	20 s		95 °C	2 s	
2	65 °C	5 s	35	65 °C	25 s	20	65 °C	10 s	24
	72 °C	5 s		72 °C	30 s		72 °C	10 s	
	95 °C	2 s		95 °C	20 s		95 °C	2 s	
3	60 °C	10 s	9	60 °C	30 s	24	60 °C	15 s	20
	72 °C	5 s		72 °C	30 s		72 °C	10 s	
4	95 °C	2 s	4	95 °C	20 s	4	95 °C	2 s	4
4	60 °C	10 s	] ]	60 °C	30 s	] 1	60 °C	15s	1
5	10 °C	stora	age	10 °C	stor	age	10 °C	stor	age



Program other thermocyclers according to Guidelines.

#### 9. DATA ANALYSIS

Detection is conducted using a fluorescence detector.



Please read the fluorescence detector Operating Manual before using this kit.

Program the detector according to the manufacturer's manual and Guidelines.

The fluorescence signal is detected in two channels:

- The signal from the *Mycoplasma genitalium* DNA is detected in the FAM channel (or analogous, depending on the detector model);
- The signal from the Internal Control is detected in the HEX channel (or analogous,

depending on the detector model).

#### Interpretation of Results

Principle of interpretation:

- Mycoplasma genitalium DNA is **detected** in a sample if its signal in the FAM channel is greater than the specified threshold value of the positive result.
- Mycoplasma genitalium DNA is not detected in a sample if the signal in the FAM
  channel is less than the specified threshold value of the negative result whereas the
  signal in the HEX channel is greater than the specified threshold value.
- The result is invalid in a sample if the signal in the FAM channel is less than the specified threshold value of the negative result whereas the signal in the HEX channel is less than the specified threshold value.
- The result is **equivocal** if the signal of a sample in the FAM channel is greater than the defined threshold value of the negative result but less than the threshold value of the positive result (the signal is between thresholds).



If the result is invalid or equivocal, the PCR should be repeated once again.

The result of the analysis is considered reliable only if the results obtained for both Positive and Negative controls of amplification as well as for the Negative control of extraction are correct (Table 2).

Table 2

#### **Results for controls**

		Result of automatic into			
Control	Stage for control	FAM channel (samples)	HEX channel (IC)	Interpretation	
C-	DNA extraction	< threshold of negative result > threshold		OK	
NCA	Amplification	< threshold of negative result		nd	
C+	Amplification	> threshold of positive result	> threshold	OK	

#### **10. TROUBLESHOOTING**

Results of analysis are not taken into account in the following cases:

- 1. The absence of positive signal in the positive control of amplification (C+) may indicate incorrect programming of the temperature profile of the thermocycler, incorrect configuration of PCR, noncompliance of the storage conditions for kit components with the manufacturer's instruction, or the expiration of the reagent kit. Check programming of the thermocycler (see 8.2.2.), storage conditions, and the expiration date of the reagents and repeat PCR once again for all samples.
- 2. If no signal was detected either in the channel for detection of the pathogen DNA or in the channel for detection of the Internal Control, the sample should be examined once

- again (PCR and detection). The same applies to the samples with equivocal results, because the fact that the specific signal does not exceed the threshold value is not sufficient to consider a sample as positive. If equivocal results are obtained in the second run, the analysis should be repeated starting from the DNA extraction stage.
- 3. Positive signal in negative controls (C- and NCA) indicates reagent or sample contamination. In this case, the results of analysis must be considered as invalid. The analyses must be repeated and measures for detecting and eliminating the contamination source must be taken.

If you have any further questions or if encounter problems, please contact our Authorized representative in the European Community.

#### 11. TRANSPORTATION

**AmpliSens®** *Mycoplasma genitalium*-FEP PCR kit should be transported at 2–8 °C for no longer than 5 days.

#### 12. STABILITY AND STORAGE

All components of the **AmpliSens**<sup>®</sup> *Mycoplasma genitalium*-FEP PCR kit are to be stored at 2–8 °C when not in use. All components of the **AmpliSens**<sup>®</sup> *Mycoplasma genitalium*-FEP PCR kit are stable until the expiration date on the label. The shelf life of reagents before and after the first use is the same, unless otherwise stated.



PCR-mix-1-FL Mycoplasma genitalium is to be kept away from light.

#### 13. SPECIFICATIONS

#### 13.1. Sensitivity

Clinical material	Transport medium	Nucleic acid extraction kit	Sensitivity, GE/ml <sup>1</sup>
Urogenital swabs	Transport Medium for Swabs (REF 956-CE, REF 987-CE) or Transport Medium with Mucolytic (REF 952-CE, REF 953-CE)	DNA-sorb-AM	1x10 <sup>3</sup>
Urine (pretreatment is — required)		DNA-sorb-AM	2x10³

<sup>&</sup>lt;sup>1</sup> Genome equivalents (GE) of the microorganism per 1 ml of the sample placed in the transport medium specified.

#### 13.2. Specificity

The analytical specificity of AmpliSens® Mycoplasma genitalium-FEP PCR kit is ensured by selection of specific primers and probes as well as stringent reaction conditions. The primers and probes were checked for possible homologies to all sequences deposited in gene banks by sequence comparison analysis. The clinical specificity of AmpliSens® Mycoplasma genitalium-FEP PCR kit was confirmed in laboratory clinical trials.

Nonspecific reactions were absent in tests with human DNA and a DNA panels of the following microorganisms: *Mycoplasma hominis; Ureaplasma urealyticum* and *U.parvum; Gardnerella vaginalis; Lactobacillus* spp.; *Escherichia coli; Staphylococcus aureus; Streptococcus pyogenes* and *S.agalactiae; Candida albicans; Neisseria flava, N.subflava, N.sicca, N.mucosa,* and *N.gonorrhoeae; Chlamydia trachomatis; Trichomonas vaginalis; Treponema pallidum; Toxoplasma gondii; HSV* types 1 and 2; *CMV;* and *HPV*.

#### 14. REFERENCES

- Handbook "Sampling, Transportation, and Storage of Clinical Material for PCR Diagnostics", developed by Federal Budget Institute of Science "Central Research Institute for Epidemiology" of Federal Service for Surveillance on Consumers' Rights Protection and Human Well-Being, Moscow, 2008.
- Guidelines "End-Point PCR Detection of STIs and Other Reproductive Tract Infections", developed by Federal Budget Institute of Science "Central Research Institute for Epidemiology" of Federal Service for Surveillance on Consumers' Rights Protection and Human Well-Being, Moscow.

#### 15. QUALITY CONTROL

In compliance with Federal Budget Institute of Science "Central Research Institute for Epidemiology" ISO 13485-Certified Quality Management System, each lot of **AmpliSens®** *Mycoplasma genitalium*-FEP PCR kit has been tested against predetermined specifications to ensure consistent product quality.

## 16. KEY TO SYMBOLS USED

REF	Catalogue number	$\triangle$	Caution
LOT	Batch code	Σ	Sufficient for
IVD	In vitro diagnostic medical device		Expiration Date
VER	Version	<b>i</b>	Consult instructions for use
	Temperature limitation		Keep away from sunlight
	Manufacturer	NCA	Negative control of amplification
	Date of manufacture	C-	Negative control of extraction
EC REP	Authorised representative in the European Community	C+	Positive control of amplification
FBIS CRIE	Federal Budget Institute of Science "Central Research Institute for Epidemiology"	IC	Internal control



# **List of Changes Made in the Instruction Manual**

VER	Location of changes	Essence of changes
02.07.11 RT	Cover page, text	The name of Institute was changed to Federal Budget Institute of Science "Central Research Institute for Epidemiology"